

Datasheet

HGM1500E Googol Diesel Power Generator

1100kW-1375kVA
1200kW-1500kVA
50Hz

Googol diesel generators are powered by Googol engines which are being manufactured by latest US based technology. Googol engines are known for cost effective reliable power solution.

Features

Googol power generators are designed to operate under extreme conditions with low operational and maintenance cost.

Honny power manufacture and test it's products under strict QC rules to insure international manufacturing standard.



Equipment

- Engine and alternator mounted on same frame steel skid.
- Build in damper for anti-vibration.
- Compact design, easy to operate and maintain.
- Sino-US Googol brand engine
- Top brand AC alternator
- Full range protections, alarms with auto shutdown features.
- Comply with ISO8628 national standard and ISO9001 quality standard. Specially designed horizontal/vertical, engine driven/electrical radiator. Industrial, Residential silencers
- Catalytic converters
- Heat exchangers
- Special spark arrester silencers
- Standard set for "CE" certification
- Sound & Weatherproof canopy optional
- Spring, seismic anti-vibration mounts
- Advanced facility for FAT.

Diesel Generator Specification

Genset Model		HGM1500E
Genset Prime Output	kW/kVA	1100/1375
Genset Standby Output	kW/kVA	1200/1500
Rating Power Factor		0.8
Rating Speed	rpm	1500
Rating Frequency	Hz	50
Rating Voltage	V	400
Engine Model		PTAA37EG5
Displacement	l	36.5
Configuration		20V
Genset Size-Open Type (LxWxH)	mm	5000x2190x2500
Genset Weight	kg	8300

Engine Data in General

Aspiration Type		Turbocharger, air-air aftercooler
Injection Type		Common rail
Configuration		Vee
No. of Cylinders		20
Displacement	l	36.5
Bore	mm	128
Stroke	mm	142
Compression Ratio		15.5:1
Piston Speed	m/s	7.1
Rotation Direction (from flywheel)		Counter Clockwise
Number of Flywheel Teeth		204
Flywheel House Size		SAE00-18

Engine Specification

Engine Model		PTAA37EG5
Speed	rpm	1500
Standby Output (LTP)	kW	1260
Prime Output (PRP)	kW	1155
Engine Continuous Power (COP)	kW	840
Fan Quantity		4
All Fans Reduction	kW	4*11
Engine Net Standby Output (LTP)	kW	1260
Engine Net Prime Output (PRP)	kW	1155
Engine Net Continuous Output (COP)	kW	840
Typical Generation Standby Output	kW	1200
Typical Generation Prime Output	kW	1100
Typical Generation Continuous Output	kW	800
Typical Alternator Efficiency	%	95.30%
Rating Power Factor		0.8
Speed droop (static) elect. Gov.		0-5%
Governing standards to ISO 8528		G3
Max. step load acceptance, 1st step (% PRP)		50%

Lubrication System

Lube Oil Specification		AFI-CG4
Oil Capacity	l	60
Max. Permissible Oil Temperature	°C	110
Oil Pressure Warning	kPa	200
Oil Pressure Shutdown	kPa	160
Oil Consumption (as % of fuel consumption)	%	≤0.5

Electrical System

Charging Alternator Voltage	V	28
Charging Alternator Capacity	A	35
Starting Voltage	V	24
Starting Motor Capacity	kW	1*9
Minimum Battery Capacity	Ah	4*150

Fuel System

Governor Type		Common Rail
Fuel Consumption at 25% of PRP	l/h	73
Fuel Consumption at 50% of PRP	l/h	137
Fuel Consumption at 75% of PRP	l/h	198
Fuel Consumption at 100% PRP	l/h	268
Lowest Fuel Consumption Ratio	g/kW.hr	204

Intake & Exhaust System

Combustion Air Consumption	m ³ /min	96
Max. Intake Restriction	KPa	5
Exhaust Temperature (Before Turbo)	°C	705
Exhaust Temperature (After Turbo)	°C	555
Max. Exhaust Back Pressure	KPa	5
Exhaust Gas Flow	m ³ /min	118.00
Turbo Bellows Diameter	mm	DN200
Exhaust Flange Diameter	mm	DN200

Cooling System

Coolant Capacity for Engine	l	40
Max. Permissible Temperature	°C	90
Max. Coolant Warning Temperature	°C	95
Max. Coolant Shutdown Temperature	°C	105
Thermostat Open Temperature	°C	71
Radiator Cooling Flow	m ³ /min	2000
Flow of Cylinder liner Coolant pump	m ³ /h	60
Heat dissipation (engine radiator)	kW	601
Heat dissipation (convection)	kW	89

Alternator Specification

Generator Model		GP1400-4P
Voltage of Genset	V	400
Rating Speed	rpm	1500
Frequency	Hz	50
Capacity @ 0.8PF, H Rise Class	kW	1120
Efficiency @ 0.8PF	%	95.3
Duty		S1
Bearing		Single
Insulation		H
Rise Temperature		H
Enclosure		IP23
Over speed	rpm	2250
Excitation System		AVR
AVR Model		MX321
Poles		4

Performance Parameter

Frequency

Frequency Droop	%	≤5
Steady-state Frequency Band	%	≤0.5
Related Downward Range of Frequency Setting	%	≥2.5
Related Upward Range of Frequency Setting	%	≥+2.5
Change Rate of Frequency Setting	%	0.2 ~ 1

Transient Frequency Deviation

100% sudden power decrease	%	≤10
Sudden Power Increase	%	≤7
100% sudden power decrease	%	≤+10
Sudden Power Increase	%	≤-7
Frequency Recovery Time	sec	≤3
Related Frequency Tolerance Band	%	2

Voltage

Steady-state Voltage Deviation	%	≤±1
Voltage Unbalance	%	1
Range of Voltage Setting	%	±5
Change Rate of Voltage Setting	%	0.2 ~1

Transient Voltage Deviation

100% Sudden Power Decrease	%	≤+20
Sudden Power Increase	%	≤-15
Voltage Recovery Time	s	≤2

Voltage Waveform & EMC Compatibility

Sin. Distortion	%	4
Coefficient Variation	%	5
Individual Harmonic Content	%	2
Radio Interference THF	%	≤2

Guangdong Honny Power-tech Co., Ltd.
 Tel: 0086-769-2278 0359
 Fax: 0086-769-2278 0357
 Email: sales@honnypower.com
 Website: www.honnypower.com
 Address: No.2, Industry North Road, Songshan Lake, Dongguan, China

