

## Datasheet

### HGM550 Googol Diesel Power Generator

**400kW- 500kVA**  
**440kW- 550kVA**  
**50Hz**

Googol diesel generators are powered by Googol engines which are being manufactured by latest US based technology. Googol engines are known for cost effective reliable power solution.

#### Features

Googol power generators are designed to operate under extreme conditions with low operational and maintenance cost.

Honny power manufacture and test it's products under strict QC rules to insure international manufacturing standard.



#### Equipment

- Engine and alternator mounted on same frame steel skid.
- Build in damper for anti-vibration.
- Compact design, easy to operate and maintain.
- Sino-US Googol brand engine
- Top brand AC alternator
- Full range protections, alarms with auto shutdown features.
- Comply with ISO8628 national standard and ISO9001 quality standard. Specially designed horizontal/vertical, engine driven/electrical radiator. Industrial, Residential silencers
- Catalytic converters
- Heat exchangers
- Special spark arrester silencers
- Standard set for "CE" certification
- Sound & Weatherproof canopy optional
- Spring, seismic anti-vibration mounts
- Advanced facility for FAT.

## Diesel Generator Specification

<b>Genset Model</b>		<b>HGM550</b>
Genset Prime Output	kW/kVA	400/500
Genset Standby Output	kW/kVA	440/550
Rating Power Factor		0.8
Rating Speed	rpm	1500
Rating Frequency	Hz	50
Rating Voltage	V	400
Engine Model		PTAA780G5
Displacement	l	12.8
Configuration		6 in line
Genset Size-Open Type (LxWxH)	mm	3400x1450x1900
Genset Weight	kg	3200

## Engine Data in General

Aspiration Type		Turbocharger, air-air aftercooler
Injection Type		Direct Injection
Configuration		In line
No. Of Cylinders		6
Displacement	l	12.8
Bore	mm	128
Stroke	mm	166
Compression Ratio		15.5:1
Piston Speed	m/s	8.3
Rotation Direction (from Flywheel)		Counter Clockwise
Number of Flywheel Teeth		160
Flywheel House Size		SAE1-14

## Engine Specification

<b>Engine Model</b>		<b>PTAA780G5</b>
Speed	rpm	1500
Engine Standby Output (LTP)	kW	486
Engine Prime Output (PRP)	kW	445
Engine Continuous Power (COP)	kW	320
Fan Reduction	kW	14
Engine Net Standby Output (LTP)	kW	472
Engine Net Prime Output (PRP)	kW	431
Engine Net Continuous Output (COP)	kW	306
BMEP for Standby Output	bar	29.72
BMEP for Prime Output	bar	27.13
BMEP for Continuous Output	bar	19.6
Typical Generation Standby Output	kW	440
Typical Generation Prime Output	kW	400
Typical Generation Continuous Output	kW	290
Typical Alternator Efficiency		94.4%
Power Factor		0.8
Speed Droop (Static) Elect. Gov.		0-5%
Governing Standards to ISO 8528		G3
Max. Step Load Acceptance, 1st Step		50%

## Lubrication System

Lube Oil Specification		AFI-CG4
Oil Capacity	l	40
Max. Permissible Oil Temperature	°C	110
Oil Pressure Warning	kPa	200
Oil Pressure Shutdown	kPa	160
Oil Consumption (as % of Fuel Consumption)	%	≤0.5

## Electrical System

Charging Alternator Voltage	V	28
Charging Alternator Capacity	A	55
Starting Voltage	V	24
Starting Motor Capacity	kW	1*6.6
Minimum Battery Capacity (Ref. Varta Brand)	Ah	2*150

## Fuel System

Governor Type		Electrical
Fuel Consumption at 25% of PRP	l/h	34
Fuel Consumption at 50% of PRP	l/h	57
Fuel Consumption at 75% of PRP	l/h	81
Fuel Consumption at 100% of PRP	l/h	107
Lowest Fuel Consumption Ratio	g/kW.hr	201

## Intake & Exhaust System

Combustion Air Consumption	m <sup>3</sup> /min	38.0
Max. Intake Restriction	KPa	5
Exhaust Temperature (Before Turbo)	°C	690
Exhaust Temperature (After Turbo)	°C	555
Max. Exhaust Back Pressure	Kpa	5
Exhaust Gas Flow	m <sup>3</sup> /min	50
Turbo Bellows Diameter	mm	DN100-150
Exhaust Flange Diameter	mm	DN150

## Cooling System

Coolant Capacity for Engine	l	18
Max. Permissible Temperature	°C	90
Max. Coolant Warning Temperature	°C	95
Max. Coolant Shutdown Temperature	°C	105
Thermostat Open Temperature	°C	79
Radiator Cooling Flow	m <sup>3</sup> /min	450
Flow of Coolant Pump	m <sup>3</sup> /h	19.7
Heat Dissipation (Engine Radiator)	kW	235
Heat Dissipation (Convection)	kW	36

## Alternator Specification

<b>Generator Model</b>		<b>GP500-4P</b>
Voltage of Genset	V	400
Rating Speed	rpm	1500
Frequency	Hz	50
Capacity @ 0.8PF, H Rise Class	%	400
Efficiency @ 0.8PF		94.9
Duty		S1
Bearing		Single
Insulation		H
Rise Temperature		H
Enclosure		IP23
Over speed	rpm	2250
Excitation System		AVR
AVR Model		SX440
Poles		4

**Performance Parameter**

**Frequency**

Frequency Droop	%	≤5
Steady-state Frequency Band	%	≤0.5
Related Downward Range of Frequency Setting	%	≥2.5
Related Upward Range of Frequency Setting	%	≥+2.5
Change Rate of Frequency Setting	%	0.2 ~ 1

**Transient Frequency Deviation**

100% Sudden Power Decrease	%	≤10
Sudden Power Increase	%	≤7
100% Sudden Power Decrease	%	≤+10
Sudden Power Increase	%	≤-7
Frequency Recovery Time	sec	≤3
Related Frequency Tolerance Band	%	2

**Voltage**

Steady-state Voltage Deviation	%	≤±1
Voltage Unbalance	%	1
Range of Voltage Setting	%	±5
Change Rate of Voltage Setting	%	0.2 ~1

**Transient Voltage Deviation**

100% Sudden Power Decrease	%	≤+20
Sudden Power Increase	%	≤-15
Voltage Recovery Time	s	≤2

**Voltage Waveform & EMC**

Sin. Distortion	%	4
Coefficient Variation	%	5
Individual Harmonic Content	%	2
Radio Interference THF	%	≤2

Guangdong Honny Power-tech Co., Ltd.  
 Tel: 0086-769-2278 0359  
 Fax: 0086-769-2278 0357  
 Email: [sales@honnypower.com](mailto:sales@honnypower.com)  
 Website: [www.honnypower.com](http://www.honnypower.com)  
 Address: No.2, Industry North Road, Songshan Lake, Dongguan, China

