

Datasheet

HGM688 Googol Diesel Power Generator

500kW-625kVA
550kW-687.5kVA
50Hz

Googol diesel generators are powered by Googol engines which are being manufactured by latest US based technology. Googol engines are known for cost effective reliable power solution.

Features

Googol power generators are designed to operate under extreme conditions with low operational and maintenance cost.

Honny power manufacture and test it's products under strict QC rules to insure international manufacturing standard.



Equipment

Engine and alternator mounted on same frame steel skid.
Build in damper for anti-vibration.
Compact design, easy to operate and maintain.
Sino-US Googol brand engine
Top brand AC alternator
Full range protections, alarms with auto shutdown features.
Comply with ISO8628 national standard and ISO9001 quality standard. Specially designed horizontal/vertical, engine driven/electrical radiator. Industrial, Residential silencers
Catalytic converters
Heat exchangers
Special spark arrester silencers
Standard set for "CE" certification
Sound & Weatherproof canopy optional
Spring, seismic anti-vibration mounts
Advanced facility for FAT.

Diesel Generator Specification

Genset Model		HGM688
Genset Prime Output	kW/kVA	500/625
Genset Standby Output	kW/kVA	550/687.5
Rating Power Factor		0.8
Rating Speed	rpm	1500
Rating Frequency	Hz	50
Rating Voltage	V	400
Engine Model		PTAA1120-G3
Displacement	l	18.3
Configuration		10V
Genset Size-Open Type (LxWxH)	mm	3300x1450x2100
Genset Weight	kg	3800

Engine Data in General

Aspiration Type		Turbocharger, air-air aftercooler
Injection Type		Direct Injection
Configuration		Vee
No. Of Cylinders		10
Displacement	l	18.3
Bore	mm	128
Stroke	mm	142
Compression Ratio		15:1
Piston Speed	m/s	7.1
Rotation Direction (from Flywheel)		Counter Clockwise
Number of Flywheel Teeth		160
Flywheel House Size		SAE1-14

Engine Specification

Engine Model		PTAA1120-G3
Speed	rpm	1500
Engine Standby Output (LTP)	kW	625
Engine Prime Output (PRP)	kW	570
Engine Continuous Power (COP)	kW	440
Fan Reduction	kW	28
Engine Net Standby Output (LTP)	kW	597
Engine Net Prime Output (PRP)	kW	542
Engine Net Continuous Output (COP)	kW	412
BMEP for Standby Output	bar	26.8
BMEP for Prime Output	bar	24.48
BMEP for Continuous Output	bar	18.92
Typical Generation Standby Output	kW	550
Typical Generation Prime Output	kW	500
Typical Generation Continuous Output	kW	380
Typical Alternator Efficiency		94.1%
Power Factor		0.8
Speed Droop (Static) Elect. Gov.		0-5%
Governing Standards to ISO 8528		G3
Max. Step Load Acceptance, 1st Step		54.0%

Lubrication System

Lube Oil Specification		AFI-CG4
Oil Capacity	l	34
Max. Permissible Oil Temperature	°C	110
Oil Pressure Warning	kPa	200
Oil Pressure Shutdown	kPa	160
Oil Consumption (as % of Fuel Consumption)	%	≤0.5

Electrical System

Charging Alternator Voltage	V	28
Charging Alternator Capacity	A	35
Starting Voltage	V	24
Starting Motor Capacity	kW	1*6.6
Minimum Battery Capacity (Ref. Varta Brand)	Ah	2*150

Fuel System

Governor Type		Electrical
Engine Output at PRP	kW	570
Fuel Consumption at 25% of PRP	l/h	44
Fuel Consumption at 50% of PRP	l/h	74
Fuel Consumption at 75% of PRP	l/h	106
Fuel Consumption at 100% of PRP	l/h	139
Lowest Fuel Consumption Ratio	g/kW.hr	203

Intake & Exhaust System

Combustion Air Consumption	m ³ /min	45
Max. Intake Restriction	KPa	5
Exhaust Temperature (Before Turbo)	°C	680
Exhaust Temperature (After Turbo)	°C	525
Max. Exhaust Back Pressure	Kpa	5
Exhaust Gas Flow	m ³ /min	53
Turbo Bellows Diameter	mm	DN150
Exhaust Flange Diameter	mm	DN150

Cooling System

Coolant Capacity for Engine	l	21
Max. Permissible Temperature	°C	90
Max. Coolant Warning Temperature	°C	95
Max. Coolant Shutdown Temperature	°C	105
Thermostat Open Temperature	°C	79
Radiator Cooling Flow	m ³ /min	688
Flow of Coolant Pump	m ³ /h	42
Heat Dissipation (Engine Radiator)	kW	293
Heat Dissipation (Convection)	kW	44

Alternator Specification

Generator Model		GP625-4P
Voltage of Genset	V	400
Rating Speed	rpm	1500
Frequency	Hz	50
Capacity @ 0.8PF, H Rise Class	kW	500
Efficiency @ 0.8PF	%	94.1
Duty		S1
Bearing		Single
Insulation		H
Rise Temperature		H
Enclosure		IP23
Over speed	rpm	2250
Excitation System		AVR
AVR Model		SX440
Poles		4

Performance Parameter

Frequency

Frequency Droop	%	≤5
Steady-state Frequency Band	%	≤0.5
Related Downward Range of Frequency Setting	%	≥2.5
Related Upward Range of Frequency Setting	%	≥+2.5
Change Rate of Frequency Setting	%	0.2 ~ 1

Transient Frequency Deviation

100% Sudden Power Decrease	%	≤10
Sudden Power Increase	%	≤7
100% Sudden Power Decrease	%	≤+10
Sudden Power Increase	%	≤-7
Frequency Recovery Time	sec	≤3
Related Frequency Tolerance Band	%	2

Voltage

Steady-state Voltage Deviation	%	≤±1
Voltage Unbalance	%	1
Range of Voltage Setting	%	±5
Change Rate of Voltage Setting	%	0.2 ~1

Transient Voltage Deviation

100% Sudden Power Decrease	%	≤+20
Sudden Power Increase	%	≤-15
Voltage Recovery Time	s	≤2

Voltage Waveform & EMC

Sin. Distortion	%	4
Coefficient Variation	%	5
Individual Harmonic Content	%	2
Radio Interference THF	%	≤2

Guangdong Honny Power-tech Co., Ltd.
 Tel: 0086-769-2278 0359
 Fax: 0086-769-2278 0357
 Email: sales@honnypower.com
 Website: www.honnypower.com
 Address: No.2, Industry North Road, Songshan Lake, Dongguan, China

