

Datasheet

HGM2750 Googol Diesel Power Generator

2000kW-2500kVA
2200kW-2750kVA
50Hz

Googol diesel generators are powered by Googol engines which are being manufactured by latest US based technology. Googol engines are known for cost effective reliable power solution.

Features

Googol power generators are designed to operate under extreme conditions with low operational and maintenance cost.

Honny power manufacture and test it's products under strict QC rules to insure international manufacturing standard.



Equipment

- Engine and alternator mounted on same frame steel skid.
- Build in damper for anti-vibration.
- Compact design, easy to operate and maintain.
- Sino-US Googol brand engine
- Top brand AC alternator
- Full range protections, alarms with auto shutdown features.
- Comply with ISO8628 national standard and ISO9001 quality standard. Specially designed horizontal/vertical, engine driven/electrical radiator. Industrial, Residential silencers
- Catalytic converters
- Heat exchangers
- Special spark arrester silencers
- Standard set for "CE" certification
- Sound & Weatherproof canopy optional
- Spring, seismic anti-vibration mounts
- Advanced facility for FAT.

Diesel Generator Specification

Genset Model		HGM2750
Genset Prime Output	kW/kVA	2000/2500
Genset Standby Output	kW/kVA	2200/2750
Rating Power Factor		0.8
Rating Speed	rpm	1500
Rating Frequency	Hz	50
Rating Voltage	V	400
Engine Model		QTA4320-G7
Displacement	l	70.8
Configuration		16V
Genset Size-Open Type (LxWxH)	mm	6200x2220x3300
Genset Weight	kg	13800

Engine Data in General

Aspiration Type		Turbocharger, air-water aftercooler
Injection Type		Direct Injection
Configuration		Vee
No. of Cylinders		16
Displacement	l	70.8
Bore	mm	170
Stroke	mm	195
Compression Ratio		13.5:1
Piston Speed	m/s	9.75
Rotation Direction (from Flywheel)		Counter Clockwise
Number of Flywheel Teeth		218
Flywheel House Size		SAE00-21

Engine Specification

Engine Model		QTA4320-G7
Speed	rpm	1500
Standby Output (LTP)	kW	2442
Prime Output (PRP)	kW	2220
Engine Continuous Power (COP)	kW	1776
Fan Reduction	kW	100
Engine Net Standby Output (LTP)	kW	2342
Engine Net Prime Output (PRP)	kW	2120
Engine Net Continuous Output (COP)	kW	1676
BMEP for Standby Output	bar	25.93
BMEP for Prime Output	bar	23.58
BMEP for Continuous Output	bar	18.86
Typical Generation Standby Output	kW	2200
Typical Generation Prime Output	kW	2000
Typical Generation Continuous Output	kW	1600
Typical Alternator Efficiency		95.8%
Rating Power Factor		0.8
Speed droop (static) elect. Gov.		0-5%
Governing standards to ISO 8528		G3
Max. step load acceptance, 1st step		45%

Lubrication System

Lube Oil Specification		AFI-CG4
Oil Capacity	l	240
Max. Permissible Oil Temperature	°C	110
Oil Pressure Warning	kPa	300
Oil Pressure Shutdown	kPa	200
Oil Consumption (as % of fuel consumption)	%	≤0.5

Electrical System

Charging Alternator Voltage	V	28
Charging Alternator Capacity	A	55
Starting Voltage	V	24
Starting Motor Capacity	kW	2*13
Minimum Battery Capacity (Ref. Varta brand)	Ah	4*200

Fuel System

Governor Type		Electrical
Fuel Consumption at 25% of PRP	l/h	164
Fuel Consumption at 50% of PRP	l/h	273
Fuel Consumption at 75% of PRP	l/h	390
Fuel Consumption at 100% of PRP	l/h	515
Lowest Fuel Consumption Ratio	g/kW.hr	194

Intake & Exhaust System

Combustion Air Consumption	m ³ /min	250
Max. Intake Restriction	KPa	5
Exhaust Temperature (Before Turbo)	°C	670
Exhaust Temperature (After Turbo)	°C	545
Max. Exhaust Back Pressure	Kpa	5
Exhaust Gas Flow	m ³ /min	626
Turbo Bellows Diameter	mm	DN250
Exhaust Flange Diameter	mm	DN250

Cooling System

Coolant Capacity for Engine	l	140
Max. Permissible Temperature	°C	90
Max. Coolant Warning Temperature	°C	95
Max. Coolant Shutdown Temperature	°C	98
Thermostat Open Temperature	°C	71
Radiator Cooling Flow	m ³ /min	3200
Flow of Cylinder liner Coolant pump	m ³ /h	75
Flow of aftercooler Coolant pump	m ³ /h	90
Heat dissipation (engine radiator)	kW	780
Heat dissipation (CAC)	kW	483
Heat dissipation (convection)	kW	121

Alternator Specification

Generator Model		GP2500-4P
Voltage of Genset	V	400
Rating Speed	rpm	1500
Frequency	Hz	50
Capacity @ 0.8PF, H Rise Class	kW	2000
Efficiency @ 0.8PF	%	95.8
Duty		S1
Bearing		Single
Insulation		H
Rise Temperature		H
Enclosure		IP23
Over Speed	rpm	2250
Excitation System		AVR
AVR Model		MX321
Poles		4

Performance Parameter

Frequency

Frequency Droop	%	≤5
Steady-state Frequency Band	%	≤0.5
Related Downward Range of Frequency Setting	%	≥2.5
Related Upward Range of Frequency Setting	%	≥+2.5
Change Rate of Frequency Setting	%	0.2 ~ 1

Transient Frequency Deviation

100% Sudden Power Decrease	%	≤10
Sudden Power Increase	%	≤7
100% Sudden Power Decrease	%	≤+10
Sudden Power Increase	%	≤-7
Frequency Recovery Time	sec	≤3
Related Frequency Tolerance Band	%	2

Voltage

Steady-state Voltage Deviation	%	≤±1
Voltage Unbalance	%	1
Range of Voltage Setting	%	±5
Change Rate of Voltage Setting	%	0.2 ~1

Transient Voltage Deviation

100% Sudden Power Decrease	%	≤+20
Sudden Power Increase	%	≤-15
Voltage Recovery Time	s	≤2

Voltage Waveform & EMC Compatibility

Sin. Distortion	%	4
Coefficient Variation	%	5
Individual Harmonic Content	%	2
Radio Interference THF	%	≤2

Guangdong Honny Power-tech Co., Ltd.

Tel: 0086-769-2278 0359

Fax: 0086-769-2278 0357

Email: sales@honnypower.com

Website: www.honnypower.com

Address: No.2, Industry North Road, Songshan Lake, Dongguan, China



BUREAU
VERITAS